

# LV190N Specification

Model	LV190N
CPU	<ul style="list-style-type: none"> <li>Intel® Core 2 Duo Desktop Processor E6300, E6400 (1.86/2.13GHz, 65nm, FSB1066, 2MB L2 cache, LGA775 package)</li> <li>Intel® Core 2 Duo Desktop Processor E6600, E6700 (2.40/2.67GHz, 65nm, FSB1066, 4MB L2 cache, LGA775 package)</li> </ul>
Core Logic	<ul style="list-style-type: none"> <li>Intel® G965 + ICH8-DH</li> </ul>
Display	<ul style="list-style-type: none"> <li>19" wide screen for TV watching for WSXGA+ 1440x900</li> <li>64-bit wide DDRII data channels</li> </ul>
Memory	<ul style="list-style-type: none"> <li>Two 200-pin SODIMM sockets, supporting DDRII 533/667</li> <li>Expandable Memory up to 4GB, based on 256/512/1024/2048MB SODIMM Module</li> </ul>
Video Controller	<ul style="list-style-type: none"> <li>Intel G965 integration</li> <li>share memory architecture, up to 256MB of Dynamic Video Memory Allocation</li> <li>support DirectX 9.0C for windows XP 3D graphics engine accelerator</li> </ul>
Storage	<ul style="list-style-type: none"> <li>Two changeable 3.5" 26mm(H) HDD; support 2nd RAID SATA2 HDD (RAID 0/1 support)</li> <li>(Factory Option) One Bay: Combo drive / DVD Dual 12.7mm(H)</li> </ul>
Keyboard	<ul style="list-style-type: none"> <li>RF Full-size keyboard with Numeric pad; Multi-Language support</li> <li>RF mouse</li> <li>Receiver dongle USB I/F</li> </ul>
Sound System	<ul style="list-style-type: none"> <li>Support 7.1CH audio output via S/PDIF port</li> <li>Integrated Azalia compliant interface</li> <li>3D stereo enhanced sound system</li> <li>Sound-Blaster PRO™ Compatible</li> <li>S/PDIF output</li> <li>1x Built-in Microphone</li> <li>1x Built-in 6W Sub-woofer</li> <li>2x Built-in 3W Speakers</li> </ul>
I/O Ports	<ul style="list-style-type: none"> <li>4x USB 2.0 ports</li> <li>1x USB 2.0 ports (for RF KB and RF Mouse)</li> <li>1x E-SATA port</li> <li>1x Mini IEEE1394a port</li> <li>4x Audio jack (Microphone, Line in, Headphone, S/PDIF out)</li> <li>1x AV IN</li> <li>1x S-Video in</li> <li>2x CATV input jack for TV Tuner cards</li> <li>1x RJ-45 jack</li> <li>1x RJ-11 jack</li> <li>1x Brightness button</li> <li>1x Power switch</li> <li>1x A.P. Key</li> <li>1x CIR port</li> <li>1x DC-in jack</li> </ul>
Slot	<ul style="list-style-type: none"> <li>7-in-1 card reader (MS/MS Pro/MS Duo/SD/Mini-SD/Mini-SD/MMC/RSMMC)</li> <li>One ExpressCard 54(34) slot</li> </ul>
Communication	<ul style="list-style-type: none"> <li>(Option) Azalia MDC 56K Plug &amp; Play Fax/Modem V1.5 Compliant</li> <li>1GB Fast Ethernet</li> <li>(Option) Intel® Wireless LAN module 3945ABG with PCIE interface</li> <li>(Factory Option) Bluetooth™ V2.0</li> <li>(Factory Option) Video camera with USB interface (1.3M pixel)</li> <li>11 Hot keys for Internet and Multimedia via RF KB</li> </ul>
Power	<ul style="list-style-type: none"> <li>Full Range AC adapter 180W AC in 100~240V, 47~63Hz</li> </ul>
Security	<ul style="list-style-type: none"> <li>Kensington® Lock</li> </ul>
Dimension	<ul style="list-style-type: none"> <li>625.5(W) x 396.9(D) x 110(H)mm (include Hinge)</li> <li>approximated to 11KG</li> </ul>
Options	<ul style="list-style-type: none"> <li>Intel Mini PCI-Express Wireless Card 3945ABG</li> <li>802.11b+g Mini Card (USB) WLAN</li> <li>Bluetooth USB v2.0</li> <li>USB FDD</li> <li>2nd RAID SATA HDD</li> <li>Azalia MDC 56K Plug &amp; Play Fax/Modem</li> <li>Hybride 2005 TV-Tuner Card</li> <li>RF KB and RF Mouse, and USB Receiver (BTC)</li> </ul>

\*\* Battery Life may vary depending on applications and configuration.

The specifications in gray are not available yet.

The content is subject to change without notice. Other brand and product names are trademarks and/or registered trademarks of their respective companies.